

TOYECORPORATION TOYE

ACCESS CONTROL SYSTEMS

P.O. Box 3997, Chatsworth, CA 91313-3997, Phone (818)-882-4000, Fax (818)-882-5325, www.toyecorp.com

Emergency Toggle Software Instructions

Optional Access Anywhere software can accommodate two mutually exclusive modes, one for normal operation, and one for emergencies.

A separate program: Emergency.mdb is used to toggle the two modes. Emergency.mdb may reside in any subdirectory, or on any PC networked to the Access Anywhere program.

This means that the emergency mode may be enabled from any PC. Emergency.mdb has its own database password which may be changed by the user. If the emergency mode is enabled, it can only restore normal operation using Emergency.mdb.

If Emergency.mdb does not reside on the same PC as does Access Anywhere, its Hyperlinks must be edited to reflect the path to Access Anywhere (Access Central.mdb).

The definition file for the emergency mode is maintained in the following subdirectory: c:\emergencydefs. If this subdirectory does not exist, it must be created. When created, it must contain two files which must be copied from c:\tc85dir:

c:\tc85dir\defs.bas and c:\tc85dir\tclparms.dta.

To define an emergency scenario, press the button to switch the focus of this program to c:\emergencydefs (after you have completed the above).

Proceed to define your system definitions from the "Define Levels Menu"

Upon exiting each definition dialog box, select the option to:
Backup Definitions as Emergency.

The Emergency Mode must be enabled using "Emergency.mdb" which requires a password. The initial default password is: "admin".

When you have defined and saved your emergency mode, change the focus of this program back to your active system path.