

Farpointe Ranger Long-Range Reader to 412x Modules Interface Cable Wiring

7 conductor - shielded. Only 4 conductors + shield used

RG or FLS Filespecs - Doesn't matter either way

Receiver TB	Wire Color	25 Position Plug (412x end)
-------------	------------	-----------------------------

```
=====
```

3	White	7	data1 - Txmt Button 1 or 3
4	Green	10	data0 - Txmt Button 1 or 3
5	Silver	20	shield
6	Black	21	gnd
7	Red	11	+12 vdc

```
=====
```

Receiver Jumper Position: OPEN

```
=====
```